

Argus Series B740X

4K 180° dual lens Wi-Fi 6 Solar battery camera with ColorX full color night vision, smart detection, 2.4/5 GHz dual band Wi-Fi

- 180° coverage in 4K
- True full-color night vision in dim lighting
- Dual band Wi-Fi 6
- Battery/solar powered

Specifications

Video & Audio	
Image Sensor	1/1.8" CMOS sensor
Resolution	5120x1440 (8 megapixels) @15fps
Lens	f=4mm , fixed
Video Compression	H.264/H.265
Field of View	Horizontal: 180° Vertical: 50°
Infrared Night Vision	NO
Color Night Vision	With spotlights: 3pcs/2W/6500K
Frame Rate	Main stream: 10fps - 15fps (default: 15fps) Sub stream: 10fps - 15fps (default: 15fps)
Code Rate	Main stream: 1024Kbps - 4096Kbps (default: 2048Kbps) Sub stream: 256Kbps - 1024Kbps (default: 512Kbps)
Audio	Two-way audio

Power	
Battery	5000mAh rechargeable battery (Battery life varies based on settings, usage & temperature.)
Solar	Reolink Solar Panel 2 (6W)
Bluetooth Standard	
Bluetooth Standard	Bluetooth V5.0
Interface	
Power Port	USB Type-C port
SD Card Slot	Supports Max. 128GB microSD card
Reset Button	YES
Audio In/Out	Built-in microphone and speaker
Wi-Fi	
Wireless Standard	IEEE 802.11 a/b/g/n/ac/ax
Operating Frequency	2.4GHz/5GHz
Wireless Security	WPA/WPA2/WPA3
Software	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P
User Access	Max. 12 simultaneous streams (2 main & 10 sub streams)
Other Feature	
Smart Alarm	PIR detection; motion detection; person detection; vehicle detection; animal detection
PIR Detecting Distance	Adjustable, up to 10m (33ft)
PIR Detecting Angle	170° horizontal
Recording Modes	Triggered recording
Time Lapse	YES

Smart Home Compatibility	Google Assistant
Home Hub Compatibility	YES
Cloud Storage	Supports Reolink Cloud (available in selected countries)
Working Environment	
Operating Temperature	-10°C~55°C (14°F~131°F)
Operating Humidity	20% ~ 85%
Weatherproof	IP66
Mechanical	
Dimensions	128*87*80mm
Weight	400g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ .